

MX-B295-DCL

Programmable Cabinet Lock

The MICROAXS MX-B295-DCL Battery Powered Keyless Cabinet Lock provides an easy, economical solution for security and keyless access control for a wide variety of cabinet doors, drawers, storage lockers and more. Quickly and easily add/delete up to 30 individual user PIN codes with programmable keypad. Powered by 2 x AAA batteries, the need for low voltage wiring is eliminated.



Features

- Red/Blue Bi-Color LED.
- For New Installations or Retrofit of Existing Manual Cam Lock Prep.
- Vertical or Horizontal Keypad Mounting.
- Multiple Locking Cam Positions, Left/Right, Bottom.
- Programmable Multiple User Mode or 1-Time Use Mode.
- 1 Master Code: Full Programming and Control Capabilities.
- Unlock Time Programmable From 1 to 9 sec. Factory Default 3 Sec.
- Keypad Tamper Lockout: Inoperable for 10 Seconds After 3 Incorrect Code Entries.
- 2 x AAA Batteries (Included), Up to 15,000 Operations.
- Concealed Manual Key Cylinder (Replaceable), 2 Keys.
- Battery Failure Override, Apply 9V Battery to External Contacts, Enter Master Code.
- 1 Sub-Master: Limited Programming for User Codes, Maintained Unlock, Unlock Time Only.
- 30 User, 4-6 Digit PIN Codes, Must be Same Length as Master Code. Field Optional User Changeable PIN.



MX-B295-DCL

Programmable Cabinet Lock

Programming Functions Overview

- Add/Change/Delete Sub-Master Code: Performs following programs only.
- Change Master Code/Code Length: Performs all program functions.
- Select Operation Mode.
- Delete ALL User Codes.
- Reset to Factory Settings.
- Set Unlock Time.
- Add / Change User Code.
- Suspend / Restore User Code.
- Suspend / Restore ALL User Codes.
- Enable/Disable Maintained Unlock Mode

Specification

Model	MX-B295-DCL
Supplied Locking Cams	(A) 1-1/2" From Spindle Centerline (B) 1" From Spindle Centerline
Door Thickness	Up to 3/4"
Cam Mounting	5/16" Square Spindle
Hole Required for Spindle	15/16" Diameter
Battery Powered	2x AAA Batteries
Dimensions	4.75"H x 1.4"W x 0.8"D - 1.4"D w/Dia
Weight	0.4 lbs

