

MX-492PS-EDR

Emergency Door Release Pull Station Emergency Exit

The MICROAXS MX-492PS-EDR Emergency Door Release Pull Station provides immediate unlocking of perimeter doors or interior doors that are equipped with fail-safe electric locks. The MX-PS492-EDR built in alarm may be used as a local door annunciator.

The MICROAXS MX-492PS-EDR is specifically designed for emergency door release and may influence the approval of an electric locking system.



Features

- Blue housing with easy to read activation instructions avoids confusion with red fire alarm stations.
- The MICROAXS MX-492PS-EDR may initiate the release of an individual door or all doors on the same circuit.
- The MICROAXS MX-492PS-EDR may be mounted in a 2" deep single gang back box or double gang box with plaster ring cover.

Specification

Model	MX-492PS-EDR
Contacts	2-SPDT 10 Amp Contacts; 1-SPDT for lock release and 1-SPDT auxiliary contact for remote monitoring, CCTV activation or alarm activation
Replacement Glass Plates	2 Replacement glass rods included
Dimension	4.75" H x 3.25" W x 1.375" D

